

MT- Motor rating and performance curve

2630.180

Curve/Impeller No	Rated Power, kW (hp)	Rated current, A	Starting current, A	Power factor cos ϕ	Ex proof version available
220 V D, 50 Hz, 3~, 2868 r/min					
226	3.7 (5.1)	12.0	81.6	0.94	No
230 V D, 50 Hz, 3~, 2884 r/min					
226	3.7 (5.1)	12.0	85.5	0.94	No
240 V D, 50 Hz, 3~, 2895 r/min					
226	3.7 (5.1)	11.0	96.3	0.92	No
380 V D, 50 Hz, 3~, 2866 r/min					
226	3.7 (5.1)	7.1	46.2	0.95	No
400 V D, 50 Hz, 3~, 2884 r/min					
226	3.7 (5.1)	6.7	48.8	0.94	No
415 V D, 50 Hz, 3~, 2874 r/min					
226	3.7 (5.1)	6.5	43.7	0.94	No
440 V D, 50 Hz, 3~, 2893 r/min					
226	3.7 (5.1)	6.2	46.5	0.93	No
500 V D, 50 Hz, 3~, 2891 r/min					
226	3.7 (5.1)	5.4	40.7	0.93	No
550 V D, 50 Hz, 3~, 2883 r/min					
226	3.7 (5.1)	4.9	34.9	0.94	No
660 V Y, 50 Hz, 3~, 2867 r/min					
226	3.7 (5.1)	4.1	26.8	0.94	No
690 V Y, 50 Hz, 3~, 2883 r/min					
226	3.7 (5.1)	3.9	28.1	0.94	No
1000 V Y, 50 Hz, 3~, 2885 r/min					
226	3.7 (5.1)	2.7	18.1	0.94	No

Y/D starting current is approximately 1/3 of D starting current.

